

Emergency generator 40 kVA as backup generator BF 4 M 2011 in RAL 7046 telegrey 2 with 100 liter tank

Completion:

Generating Set:	stationary	Gen Set:	silent Set
------------------------	-------------------	-----------------	-------------------

Technical Data Engine:

Engine Manufacturer:	Deutz	Engine Type:	BF 4 M 2011
Engine No.:	auf Anfrage	Engine Power:	36,4 KW
Cooling:	oil-cooled	Starting:	electrical 12 V DC
Rotation:	1500 rpm	Fuel:	heating oil EN 590

Technical Data Generator:

Generator Manufacturer:	Stamford AvK	Gen Set:	Synchron mit AVR
Gen No.:	auf Anfrage	Gen Power:	40 kVA
Voltage:	400 / 231 Volt	Power Factor:	cos. - phi 0,8
Rotation:	1500 rpm		

Control Unit:

Setup:	automatic start	Functions:	Hand & Remotestart
Switch:	gen switch 4 pole	Delivery:	set up
Width ca. mm:		Depth ca. mm:	
Height ca. mm:			

Tank

Setup:	Baseframe fuel Tank with Bassin		
Width ca. mm:		Height ca. mm:	
Depth ca. mm:		Capacity / Litre:	100

Dimensions of unit:

Length ca. mm:	2.220	Height ca. mm:	1.430
Width ca. mm:	960	Weigth ca. KG:	1.050

Usage:

State:	new	year of manufacture:	2023
time of delivery:	ex work	Price plus VAT in 1/2 %:	on request:
Operating Hours:	1		
Location:	Verl - Germany		
Stock No:		Reserved:	nein / no

Delivery Contents:

General equipment Emergency generator TYPE WA DG 40 "S" 100 L | RAL 7046

Soundproof backup power supply with the following properties:

Emergency generator as backup power supply for your reliable emergency power supply with an original 4-cylinder Deutz industrial diesel engine with mechanical speed control and Stamford three-phase synchronous generator. Motor and generator are mounted elastically on a common skid frame. Exhaust system insulated with mineral fiber sheathing. Installed in a modular soundproofing enclosure. Powder-coated in RAL 7046 telegrey

Fuel consumption according to Deutz data sheet:

4.47 liters at 50% load | Running time with a full tank approx. 22.3 hours
6.66 liters at 75% load | Running time with a full tank approx. 15.0 hours
9.10 liters at 100% load | Running time with a full tank approx. 10.9 hours

Internal automatic start-stop (type: AMF DSE 4150) with display of all important engine and generator messages. Functional indication digitally on the display. Generator switch 63 amps 4 poles integrated in the unit (switchgear). Internal battery charger 230 volts - 12 volts DC

Optionally available at extra cost (1,620 euros net):

Automatic start with mains & generator switching 4-pin | 90 amps

External emergency power switchgear for installation in the building and 4-pole mains generator switchover

Function: In the event of a power failure, the start command is sent to the diesel unit. When the nominal speed and nominal voltage are reached, the generator switch is switched on. When the mains returns, the automatic system monitors the mains voltage. When this is stable again, the system switches back to mains operation. The diesel unit is stopped after the cooling time and waits in automatic mode for the next power failure.

-/-

Optional, available at extra cost: (subject to availability)

CEE socket 63 ampere 1H coded attached to the unit, this plug device is required for feeding into a building according to VDE 0100-551 supplement 1: 2019.06

VDE-AR-N 4100 contains additional requirements for setting up emergency power supplies for permanently installed systems (parts) that are supplied from the public grid during normal operation.

The emergency power system as an emergency power supply is ready for operation and immediately available from the Verl warehouse.

Product Images



